



OUR PRODUCTS

VOSS AUDIO AMPLIFIER SWITCHER PA-100AC



Product Features

- **5 Main Amplifier Channels + 1 Spare** – Auto-switches on fault
- **Automatic Fault Detection** – First fault unit switches to spare
- **Manual Mode** – For upgrades and maintenance
- **Status Indicators** – Normal (green), Fault (red), Spare (yellow)
- **Prompt Tone** – Rings on main amplifier failure; mute button available
- **Sensitivity Controls** – Adjust detector sensitivity
- **Reset Button** – Resume main amplifier (manual mode)
- **Audio Inputs** – CH1-CH5 for main amplifiers
- **Audio Outputs** – CH1-CH5 to main amplifiers; spare output to spare amplifier
- **Amplified Signal Inputs** – CH1-CH5 (100V&COM or 70V&COM)
- **Standby Amplified Input** – From standby amplifier
- **Speaker Outputs** – For connecting speakers
- **Power Supply** – DC24V or AC100~240V, 50/60Hz
- **Power Consumption** – 20~25W
- **Channel Capacity** – 150V/20A, audio signal
- **Input / Output Signal** – 0.775V (0dB), 10k Ω , unbalanced
- **Dimensions** – 89 × 483 × 350 mm
- **Net Weight** – 6.9 kg