

Public Address Amplifier MA-80W / MA-120W



Specification

Model	MA-80W	MA-120W
Power output	80W	120W
Versatile	support Bluetooth / radio / MP3 playback	
Input sensitivity	AUX 250mV (unbalanced) MIC5mV (unbalanced)	
Gain adjustment range	BASS: ± 10 dB (100Hz), TREBLE: ± 10 dB (10KHz)	
Total harmonic distortion	<0.1% at 1kHz, 3/1 rated power output	
Signal to noise ratio	MIC: 66dB, AUX: 70dB	
Priority level	MIC1 has the highest priority	
Frequency response	50-16KHz ± 2 dB	
Output adjustment rate	<3dB	
Auxiliary output	unbalanced lotus output 0.775V	
Protection function	over temperature, over current, overload, short circuit	
Power supply	AC 220-240V, 50Hz-60Hz	
Input voltage:	70 / 100V	
Product size:	260 X180 X 65 MM	