

VOSS AUDIO PROFESSIONAL AUDIO DIGITAL MIXER T-24



Product Description

- 24 Channels Input (24 MIC Input and 1 Stereo Input) Digital Input: Optical Fiber/Sound Card and MP3
- Input channel sound balance adjustment
- MIC input digital gain Input
- +48V phantom power (MIC channel ON/OFF Independently)
- Built-in compressor, high and low pass filter, 5 segment parameter equalization, delay, Input channel sound balance adjustment
- Input and Output EQ ON/OFF
- Multi-functional button
- Each channel has Multi-functional menu, mute, monitor button
- Each channel with 100MM motorized fader, signal light, peak light (33 motorized faders)
- 12 channels output (Main output L,R 6 Aux output, 4 group output)
- AUX Output (Pre fader, Post fader)
- Output processing: High and low pass filter, 15 Segment Parameter Balance (T20/24/32), 12 segments Parameter Balance (T-16); compressor, delay phase
- Digital recording function; Double row, 3 color, 12 stage level indicator light.
- Built-in Sound Card (MP3, PC Play music directly); 4 shortcut scene transfer mode, 100 scene storage
- User parameter storage and transfer (can be managed on PC); Built-in dual DSP effect;
- FX pedal witch interface ; Multi operating system manipulation software (ISO System, Windows system), English/Chinese
- Optical fiber Input and Output; 7 Inch 800*490 High-definition
- Net Size : T-24: (63.7*5*21.5*51.5cm)
- N.W. 13KG