

VOSS AUDIO WA-4400 POWER AMPLIFIER



Specification

Model	WA-4300		WA-4400		WA-4500		WA-4600	
	Channel A/B	Channel C/D	Channel A/B	Channel C/D	Channel A/B	Channel C/D	Channel A/B	Channel C/D
Stereo Power 8Ω	300W×2	300W×2	400W×2	400W×2	500W×2	500W×2	600W×2	600W×2
Stereo Power 4Ω	450W×2	450W×2	600W×2	600W×2	750W×2	750W×2	900W×2	900W×2
Bridge Power 8Ω	600W	600W	800W	800W	1000W	1000W	1200W	1200W
Bridge Power 4Ω	900W	900W	1200W	1200W	1500W	1500W	1800W	1800W
S/N	110dB							
Damping Factor	600:1							
Frequency Response	+/-0.1dB,20Hz-20KHz							
T.H.D	0.775V							
Sensitivity	≥-70dB							
LED Signals	Signal,Power,clip, protection							
Power Supply	~220v/50Hz							
Power Consumption	2500W		3300W		3900W		5000W	
Net Weight	23kg		24kg		26kg		28kg	
Dimension	483mm×512mm×88mm							