



OUR PRODUCTS

VOSS AUDIO DA-3000 DIGITAL PROFESSIONAL POWER AMPLIFIER



TECHNICAL PARAMETERS:

- A/B CHANNELS
- POWER (8Ω) 1500W × 2
- POWER (4Ω) 2250W × 2
- BRIDGED POWER (8Ω) 4500W
- SIGNAL-TO-NOISE RATIO 110 DB
- FREQUENCY RESPONSE (1W 8Ω) 20HZ-20KHZ ±0.5 DB
- TOTAL HARMONIC DISTORTION (20HZ-20KHZ, HALF POWER) ≤0.06%
- SENSITIVITY (8Ω 1KHZ) 0.775V / 1.0V / 1.4V
- DAMPING FACTOR (1KHZ & 8Ω) ≥900
- INPUT IMPEDANCE 20KΩ / 10KΩ
- NET WEIGHT 22.6 KG
- DIMENSIONS 483 × 336 × 89 MM